

eGrabber

eGrabber 26.09 Release Notes



This documentation is provided with **eGrabber 26.09.0** (doc build 2222).
<https://www.euresys.com>

This documentation is subject to the General Terms and Conditions stated on the website of **EURESYS S.A.** and available on the webpage <https://www.euresys.com/en/Menu-Legal/Terms-conditions>. The article 10 (Limitations of Liability and Disclaimers) and article 12 (Intellectual Property Rights) are more specifically applicable.

Contents

1. Release Benefits	4
2. Release Specification	5
2.1. Supported Products	6
2.2. Firmware Variants	9
2.3. Camera Interfaces Standard Compliance	16
2.4. Supported Operating Systems	17
2.5. Memento	19
2.6. Development Tools	20
2.7. Software Adapters	21
2.8. Software Tools	22
2.9. Online Documentation	23
3. Important Notices	24
3.1. Firmware Revisions	24
3.2. CPU Requirements	24
3.3. Image Buffer Limits	25
3.4. Notice for Linux	25
3.5. Notice for NVIDIA RDMA	25
3.6. Notices for macOS	26
3.7. Notice for Early Coaxlink Drivers	27
3.8. Notice for Coaxlink QSFP28 and Octo CXP-12 users	28
4. Release Details	29
4.1. Features Updates	30
4.2. Solved Issues	32
4.3. Changes	33
4.4. Firmware Changes	34
4.5. Breaking Changes	35
5. Known Issues	44
5.1. [PC1628] Grablink Duo Limitations	45
5.2. Deviations from the GenTL Specification	46
5.3. Deviations from the PCI Express Specification	48
5.4. GenICam Browser (Deprecated) and gentl view Limitations	48
6. Appendix	49
6.1. Firmware Variants History	49
6.2. Operating Systems History	57
6.3. About Icons	58

1. Release Benefits

Benefits of added or improved features of eGrabber 26.09

eGrabber

[Improved GenDC support](#)

This release of **eGrabber** improves its support of GenDC with new `Buffer` and `ScopedBuffer` methods related to buffer parts.

Frame Grabbers

[\[PC1628\] Grablink Duo features set extension](#)

This release of **eGrabber**:

- Add the support new Camera Link Medium, Full, 72-bit and 80-bit tap configurations
- Extends the support of RGB cameras having more than 8-bit per component
- Adds the support of RGBa cameras
- Adds the support of new tap geometries

eGrabber Studio

[Improved support of large image](#)

This release of **eGrabber Studio** includes new "Downscaling mode" options in the advanced setup of the `Buffer` pane; these options control the downscaling of large images when the zoom level is below 100%; the "Fine" option creates higher-quality (slower) downsampled images, while the "Coarse" option creates lower-quality (faster) downsampled images, which improves the application reactivity when displaying large images.

eGrabber Recorder

[License-free application](#)

Starting with this release of **eGrabber**, **eGrabber Recorder** and **Playlink** no longer require the additional paid license ([PC4401] **eGrabber Recorder**).

2. Release Specification

- 2.1. Supported Products 6
- 2.2. Firmware Variants 9
- 2.3. Camera Interfaces Standard Compliance16
- 2.4. Supported Operating Systems17
- 2.5. Memento19
- 2.6. Development Tools20
- 2.7. Software Adapters21
- 2.8. Software Tools22
- 2.9. Online Documentation23

2.1. Supported Products

This topic shows, for each product series and sub-series, the list of officially¹ supported products by eGrabber 26.09.

- The **Product code and name** column shows the order code and the official name of the product.
- The **Class** column shows the functional class of the product (e.g.: Frame Grabber, I/O Extension ...).
- The **Icon** column shows the [product icon](#) used in this documentation package.



Camera Link products

Product code and name	Class	Icon	First release
[PC1628] Grablink Duo	Frame Grabber		eGrabber 23.02

CoaXPress CXP-6 products

Product code and name	Class	Icon	First release
[PC1629] Coaxlink Duo PCIe/104-EMB	Frame Grabber		Coaxlink 6.0
[PC1630] Coaxlink Mono	Frame Grabber		Coaxlink 2.0
[PC1631] Coaxlink Duo	Frame Grabber		Coaxlink 2.0
[PC1632] Coaxlink Quad	Frame Grabber		Coaxlink 1.0
[PC1633] Coaxlink Quad G3	Frame Grabber		Coaxlink 4.0
[PC1633-LH] Coaxlink Quad G3 LH	Frame Grabber		Coaxlink 11.1
[PC1635] Coaxlink Quad G3 DF	Frame Grabber		Coaxlink 5.0
[PC1637] Coaxlink Quad 3D-LLE	Frame Grabber		Coaxlink 9.0
[PC3602] Coaxlink Octo	Frame Grabber		Coaxlink 10.0

CoaXPress CXP-12 products

Product code and name	Class	Icon	First release
[PC3603] Coaxlink Quad CXP-12	Frame Grabber		Coaxlink 10.4
[PC3603-4] Coaxlink Quad CXP-12	Frame Grabber		eGrabber 15.0





¹ Excluding preliminary products


Product code and name	Class	Icon	First release
[PC3621] Coaxlink Mono CXP-12	Frame Grabber		Coaxlink 12.4
[PC3621-LH] Coaxlink Mono CXP-12 LH	Frame Grabber		Coaxlink 12.4
[PC3622] Coaxlink Duo CXP-12	Frame Grabber		Coaxlink 12.4
[PC3622-LH] Coaxlink Duo CXP-12 LH	Frame Grabber		Coaxlink 12.4
[PC3623] Coaxlink Quad CXP-12 Value	Frame Grabber		eGrabber 23.08
[PC3624] Coaxlink Quad CXP-12 DF	Frame Grabber		eGrabber 24.03
[PC3633] Coaxlink Quad CXP-12 3D-LLE	Frame Grabber		eGrabber 24.12

CoaXPress-over-Fiber products




Product code and name	Class	Icon	First release
[PC3625] Coaxlink QSFP+	Frame Grabber		eGrabber 17.0
[PC3628] Coaxlink QSFP28	Frame Grabber		eGrabber 25.10
[PC3629] Coaxlink CXP-12 to QSFP+ Converter	Converter		eGrabber 24.10

Accessories

Product code and name	Class	Icon	First release
[PC1625] DB25F I/O Adapter Cable	Cable Adapter		
[PC1636] InterPC C2C-Link Adapter	Adapter		Coaxlink 8.0
[PC1676] AC-DC Power Adapter, 24V, 160W	Power Adapter		eGrabber 24.10
[PC3300] HD26F I/O module for Coaxlink Duo PCIe/104	I/O Module		
[PC3301] Thermal drain (Model 1) for Coaxlink Duo PCIe/104	Heatsink		
[PC3302] DIN1.0/2.3 Coaxial cable for Coaxlink Duo PCIe/104	Cable		
[PC3303] C2C-Link Ribbon Cable	Cable		
[PC3304] HD26F I/O Adapter Cable	Cable Adapter		
[PC3610] HD26F I/O Extension Module - TTL-RS422	I/O Extension		Coaxlink 10.4
[PC3612] HD26F I/O Extension Module - TTL-CMOS5V-RS422	I/O Extension		Coaxlink 10.4
[PC3613] JTAG Adapter Xilinx for Coaxlink	Cable Adapter		

Product code and name	Class	Icon	First release
[PC3614] HD26F I/O Extension Module - Standard I/O Set	I/O Extension		Coaxlink 10.4
[PC3618] HD26F I/O Extension Module - Fast I/O	I/O Extension		

Free software

Product code and name	Class	Icon	First release
[PC4400] eGrabber Gigelink	Library Instance		eGrabber 15.0
[PC4401] eGrabber Recorder	Library Instance		eGrabber 15.1
[PC4403] eGrabber Studio	Application		eGrabber 22.03
PC4405 eGrabber Memento	Application		
PC4406 eGrabber Driver	Driver		

2.2. Firmware Variants

Content description

This topic shows the list of officially available¹ [firmware variants](#)² included in the [embedded firmware](#)³ of eGrabber 26.09.

Each section is dedicated to a [firmware set](#)⁴. It is entitled with the name of the target products group e.g. PC1633 - Coaxlink Quad G3

The blue area shows the **list of products** sharing the same firmware set.

The table shows all the firmware variants belonging to the firmware set:

- The **Firmware variant** column shows the name of the firmware variant.
- The **HCMAP** column shows the [Host Connection Map](#)⁵.
- The **Features** column shows the main features of the firmware variant using "[Features abbreviations](#)" on page 9.
- The **Description** column shows a one-phrase description of the connection scheme.
- The **Rev.** column shows the [firmware revision number](#)⁶.

See also: "[Firmware Variants History](#)" on page 49

Features abbreviations

- *BIN*: Pixel binning
- *CFA-12*: Bayer CFA decoding - Methods 1 and 2
- *CFA-123*: Bayer CFA decoding - Methods 1, 2, and 3
- *CFA-125*: Bayer CFA decoding - Methods 1, 2, and 5
- *CFA-2-S0*: Bayer CFA decoding - Method 2 on Stream0
- *CFA-3*: Bayer CFA decoding - Method 3
- *CFA-35*: Bayer CFA decoding - Methods 3 and Method 5
- *CFA-35-D0*: Bayer CFA decoding - Methods 3 and 5 on Device0
- *FLIPX*: Horizontal image flipping

¹ Excluding custom firmware variants

² A firmware instance providing a specific set of features. A firmware variant is named after the main feature. E.g.: the "1-camera, linescan" variant allows the target product(s) to connect 1 line-scan camera.

³ A collection of firmware .bit files delivered with each release of eGrabber.

⁴ A collection of firmware gathering all the variants for the same Target Product(s group). A firmware set is named as follows: PC<ProductCode> - <ProductName>. When several products share a common firmware, the reference of the product without product code suffix is used! For instance, the PC1633 - Coaxlink Quad G3 target product(s group) refers to two products: [PC1633] Coaxlink Quad G3 and [PC1633-LH] Coaxlink Quad G3 LH.

⁵ Specific assignment of the Device connections to the Host connectors

⁶ The revision number of the firmware .bit file.

- *FFC*: Flat-field correction
- *LLE*: Laser line extraction
- *LT*: Mapping of events from the I/O Toolbox to CoaXPress trigger messages LinkTrigger0 and LinkTrigger1
- *LUT*: Lookup table processing
- *MI*: Metadata insertion
- *PLANAR*: RGB to PLANAR_RGB or BGR to PLANAR_BGR conversions

PC1628 - Grablink Duo firmware set

Applies to:

[PC1628] Grablink Duo.

Duo

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D2_CL	LUT CFA-12	One 1- or 2-connection area-scan camera	533
1-camera, line-scan	1D2_CL	LUT MI PLANAR	One 1- or 2-connection line-scan camera	533
2-camera	2D11_CL	LUT CFA-12	One or two 1-connection area-scan cameras	533
2-camera, line-scan	2D11_CL	LUT MI PLANAR	One or two 1-connection line-scan cameras	533

PC1629 - Coaxlink Duo PCIe/104-EMB firmware set

Applies to:

[PC1629] Coaxlink Duo PCIe/104-EMB.

Duo104EMB ^{EOL}

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D2	LUT	One 1- or 2-connection area-scan camera	530
1-camera, line-scan	1D2	LUT	One 1- or 2-connection line-scan camera	530
2-camera	2D11	LUT	One or two 1-connection area-scan cameras	530

PC1630 - Coaxlink Mono firmware set

Applies to:

[PC1630] Coaxlink Mono.

Mono ^{EOL}

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D1	LUT	One 1-connection area-scan camera	530

PC1631 - Coaxlink Duo firmware set

Applies to:

[PC1631] Coaxlink Duo.

Duo **EOL**

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D2	LUT	One 1- or 2-connection area-scan camera	530
1-camera, line-scan	1D2	LUT	One 1- or 2-connection line-scan camera	530
2-camera	2D11	LUT	One or two 1-connection area-scan cameras	530
2-camera, line-scan	2D11	LUT	One or two 1-connection line-scan cameras	530

PC1632 - Coaxlink Quad firmware set

Applies to:

[PC1632] Coaxlink Quad.

Quad **EOL**

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D4	LUT	One 1- or 2- or 4-connection area-scan camera	530
1-camera, line-scan	1D4	LUT	One 1- or 2- or 4-connection line-scan camera	530
2-camera	2D22	LUT	One or two 1- or 2-connection area-scan cameras	530

PC1633 - Coaxlink Quad G3 firmware set

Applies to:

[PC1633] Coaxlink Quad G3 and [PC1633-LH] Coaxlink Quad G3 LH.

QuadG3 QuadG3LH

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D4	FFC LUT CFA-12	One 1- or 2- or 4-connection area-scan camera	530
1-camera, 4-data-stream	1D4S4		One 1- or 2- or 4-connection area-scan camera, up to 4 data streams	530
1-camera, line-scan	1D4	FFC LUT FLIPX	One 1- or 2- or 4-connection line-scan camera	530
2-camera	2D22	LUT CFA-35-D0	One or two 1- or 2-connection area-scan cameras	530
2-camera, bayer	2D22	CFA-35	One or two 1- or 2-connection area-scan cameras	530
2-camera, line-scan	2D22	LUT FLIPX	One or two 1- or 2-connection line-scan cameras	530
3-camera	3D211	LUT	One 1- or 2-connection and one or two 1-connection area-scan cameras	530
4-camera	4D1111	LUT	One or two or three or four 1-connection area-scan cameras	530
4-camera, line-scan	4D1111	LUT	One or two or three or four 1-connection line-scan cameras	530

PC1635 - Coaxlink Quad G3 DF firmware set

Applies to:

[PC1635] Coaxlink Quad G3 DF.

QuadG3DF ^{EOL}

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D4	LUT CFA-123	One 1- or 2- or 4-connection area-scan camera	530
1-df-camera	1DF4	LUT CFA-123	One 1- or 2- or 4-connection area-scan data-forwarded camera	530
1-camera, line-scan	1D4	FFC LUT FLIPX	One 1- or 2- or 4-connection line-scan camera	530
1-df-camera, line-scan	1DF4	FFC LUT FLIPX	One 1- or 2- or 4-connection line-scan data-forwarded camera	530

PC1637 - Coaxlink Quad 3D-LLE firmware set

Applies to:

[PC1637] Coaxlink Quad 3D-LLE.

Quad3DLLE

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D4	LUT LLE	One 1- or 2- or 4-connection area-scan camera	530
2-camera	2D22	LUT LLE	One or two 1- or 2-connection area-scan cameras	530

PC3602 - Coaxlink Octo firmware set

Applies to:

[PC3602] Coaxlink Octo.

Octo

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D8	LUT CFA-123	One 1- or 2- or 4- or 8-connection area-scan camera	530
1-camera, line-scan	1D8	LUT MI	One 1- or 2- or 4- or 8-connection line-scan camera	530
2-camera	2D44	FFC LUT CFA-125	One or two 1- or 2- or 4-connection area-scan cameras	530
2-camera, line-scan	2D44	LUT FLIPX MI PLANAR	One or two 1- or 2- or 4-connection line-scan cameras	530
3-camera	3D422	LUT	One 1- or 2- or 4-connection and one or two 1- or 2-connection area-scan cameras	530
4-camera	4D2222	LUT	One or two or three or four 1- or 2-connection area-scan cameras	530
4-camera, line-scan	4D2222	LUT MI	One or two or three or four 1- or 2-connection line-scan cameras	530
5-camera	5D41111	LUT	One 1- or 2- or 4-connection and one or two or three or four 1-connection area-scan cameras	530
5-camera, 5D22211	5D22211	LUT	One or two or three 1- or 2-connection and one or two 1-connection area-scan cameras	530
6-camera	6D221111	LUT	One or two 1- or 2-connection and one or two or three or four 1-connection area-scan cameras	530
8-camera	8D11111111	LUT	Up to eight 1-connection area-scan cameras	530
8-camera, line-scan	8D11111111	LUT MI	Up to eight 1-connection line-scan cameras	530

PC3603 - Coaxlink Quad CXP-12 firmware set

Applies to:

[PC3603] Coaxlink Quad CXP-12 and [PC3603-4] Coaxlink Quad CXP-12.

Quad12 ^{EOL} Quad12-4

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D4	FFC LUT CFA-12 BIN MI	One 1- or 2- or 4-connection area-scan camera	530
1-camera, line-scan	1D4	FFC LUT BIN MI LT	One 1- or 2- or 4-connection line-scan camera	530
2-camera	2D22	FFC LUT MI	One or two 1- or 2-connection area-scan cameras	530
2-camera, line-scan	2D22	LUT MI LT	One or two 1- or 2-connection line-scan cameras	530
3-camera	3D211	LUT MI	One 1- or 2-connection and one or two 1-connection area-scan cameras	530
3-camera, line-scan	3D211	LUT MI	One 1- or 2-connection and one or two 1-connection line-scan cameras	530
4-camera	4D1111	LUT MI	One or two or three or four 1-connection area-scan cameras	530
4-camera, line-scan	4D1111	LUT MI	One or two or three or four 1-connection line-scan cameras	530

PC3621 - Coaxlink Mono CXP-12 firmware set

Applies to:

[PC3621] Coaxlink Mono CXP-12 and [PC3621-LH] Coaxlink Mono CXP-12 LH.

Mono12 ^{REQ} Mono12LH

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D1	LUT	One 1-connection area-scan camera	530
1-camera, line-scan	1D1	LUT	One 1-connection line-scan camera	530

PC3622 - Coaxlink Duo CXP-12 firmware set

Applies to:

[PC3622] Coaxlink Duo CXP-12 and [PC3622-LH] Coaxlink Duo CXP-12 LH.

Duo12 ^{REQ} Duo12LH

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D2	LUT CFA-3 MI	One 1- or 2-connection area-scan camera	530
1-camera, line-scan	1D2	LUT	One 1- or 2-connection line-scan camera	530
2-camera	2D11	LUT MI	One or two 1-connection area-scan cameras	530
2-camera, line-scan	2D11	LUT	One or two 1-connection line-scan cameras	530

PC3623 - Coaxlink Quad CXP-12 Value firmware set

Applies to:

[PC3623] Coaxlink Quad CXP-12 Value.

Value12

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D4	FFC LUT CFA-12 BIN MI	One 1- or 2- or 4-connection area-scan camera	530
1-camera, line-scan	1D4	FFC LUT BIN MI LT	One 1- or 2- or 4-connection line-scan camera	530
2-camera	2D22	LUT MI	One or two 1- or 2-connection area-scan cameras	530
2-camera, line-scan	2D22	LUT MI LT	One or two 1- or 2-connection line-scan cameras	530
3-camera	3D211	LUT MI	One 1- or 2-connection and one or two 1-connection area-scan cameras	530
4-camera	4D1111	LUT MI	One or two or three or four 1-connection area-scan cameras	530
4-camera, line-scan	4D1111	LUT MI	One or two or three or four 1-connection line-scan cameras	530

PC3624 - Coaxlink Quad CXP-12 DF firmware set

Applies to:

[PC3624] Coaxlink Quad CXP-12 DF.

Quad12DF

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D4	FFC LUT CFA-12 BIN	One 1- or 2- or 4-connection area-scan camera	530
1-df-camera	1DF4	FFC LUT CFA-12 BIN	One 1- or 2- or 4-connection area-scan data-forwarded camera	530
1-camera, line-scan	1D4	LUT MI	One 1- or 2- or 4-connection line-scan camera	530
1-df-camera, line-scan	1DF4	LUT MI	One 1- or 2- or 4-connection line-scan data-forwarded camera	530

PC3625 - Coaxlink QSFP+ firmware set

Applies to:

[PC3625] Coaxlink QSFP+.

QSFP+

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D4	LUT CFA-12	One 1- or 2- or 4-connection area-scan camera	530
1-camera, line-scan	1D4	LUT MI	One 1- or 2- or 4-connection line-scan camera	530
2-camera	2D22	FFC LUT	One or two 1- or 2-connection area-scan cameras	530
4-camera	4D1111	LUT	One or two or three or four 1-connection area-scan cameras	530
4-camera, line-scan	4D1111	LUT MI	One or two or three or four 1-connection line-scan cameras	530

PC3628 - Coaxlink QSFP28 firmware set

Applies to:

[PC3628] Coaxlink QSFP28.

QSFP28

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D4	LUT CFA-12	One 1- or 2- or 4-connection area-scan camera	536
1-camera, line-scan	1D4	LUT	One 1- or 2- or 4-connection line-scan camera	536

PC3629 - Coaxlink CXP-12 to QSFP+ Converter firmware set

Applies to:

[PC3629] Coaxlink CXP-12 to QSFP+ Converter.

QSFP+Conv

Firmware Variant	HCMAP	Features	Description	Rev.
1xCxp2CoFx4	1D1		One 1-connection area-scan camera	477
2xCxp2CoFx2	2D22		One or two 1- or 2-connection area-scan cameras	477
4xCxp2CoFx1	4D1111		One or two or three or four 1-connection area-scan cameras	477

PC3633 - Coaxlink Quad CXP-12 3D-LLE firmware set

Applies to:

[PC3633] Coaxlink Quad CXP-12 3D-LLE.

Quad12LLE

Firmware Variant	HCMAP	Features	Description	Rev.
1-camera	1D4	LLE	One 1- or 2- or 4-connection area-scan camera	530

2.3. Camera Interfaces Standard Compliance

CoaXPress

Coaxlink frame grabbers together with **eGrabber 26.09** comply with:

- *CoaXPress Standard 1.0*
- *CoaXPress Standard 1.1*
- *CoaXPress Standard 1.1.1*
- *CoaXPress Standard 2.0*
- *CoaXPress Standard 2.1¹*

CoaXPress-over-Fiber

[PC3625] Coaxlink QSFP+, [PC3628] Coaxlink QSFP28 and the QSFP+ port of [PC3629] Coaxlink CXP-12 to QSFP+ Converter comply with:

- *CoaXPress-over-Fiber Bridge Protocol 1.1*

Camera Link

Grablink Duo together with **eGrabber 26.09** comply with

- *Camera Link Standard 2.1²*

¹ GenICam GenDC (Generic Data Container) support is optional in CoaXPress 2.1 and is currently not included.

² Including PoCL

2.4. Supported Operating Systems

See also: ["Operating Systems History" on page 57](#)

Windows

eGrabber driver, eGrabber Studio, eGrabber Gigelink, eGrabber Recorder and GenICam Browser (Deprecated) are designed to support all versions of **Windows 10** and **Windows 11**, including the **Server** and the **IoT Enterprise** versions on **x86-64 (64-bit)** platforms.

[Minimum version requirements](#)

Windows 10 version 1809 or later

[Release validation](#)

This release has been validated with the following Windows versions:

OS Name & Version	Platform	Notes
Microsoft Windows 10	x86-64 (64-bit)	IoT Enterprise LTSC 2019 - Version 1809
		Enterprise edition - Version 1809
		Enterprise edition - Version 22H2
Microsoft Windows 11	x86-64 (64-bit)	Enterprise edition - Version 22H2
		Enterprise edition - Version 23H2
		Enterprise edition - Version 24H2
Microsoft Windows Server 2025	x86-64 (64-bit)	Standard edition - Version 24H2



NOTE

- The driver is signed by Microsoft.
- Power saving modes of the operating systems (StandBy, Sleep, Suspend...) are not supported.
- Kernel DMA Protection is not supported.

See also: [Installing eGrabber on Windows in the Getting Started section of the Coaxlink series or Grablink Duo Handbooks](#)

Linux

eGrabber driver, eGrabber Studio, eGrabber Gigelink, eGrabber Recorder and GenICam Browser (Deprecated) are designed to be distribution-independent on **x86-64 (64-bit)**, and **AArch64 (64-bit)** platforms. They are expected to work with a wide range of distributions.

[Minimum kernel version requirements](#)

All tools and libraries require kernel version 4.4 or higher

[GNU C library \(glibc\) requirements](#)

All tools and libraries require glibc library version 2.23 (or higher)

[Release validation](#)

This release has been validated with the following distribution(s):

OS Name & Version	Platform	Notes
Linux CachyOS 25.11	x86-64 (64-bit)	Kernel version 6.18.5-2
Linux Fedora 33	x86-64 (64-bit)	Kernel version 5.8.15
Linux OpenSUSE Leap 15.4	x86-64 (64-bit)	Kernel version 5.14
Linux Ubuntu 17.04	x86-64 (64-bit)	Kernel version 4.10
Linux Ubuntu 18.04	AArch64 (64-bit)	Kernel version 5.4.0-42
Linux Ubuntu 20.04 LTS	x86-64 (64-bit)	Kernel version 5.15
Linux Ubuntu 20.04.6 LTS	AArch64 (64-bit)	Kernel version 5.10.216-tegra
Linux Ubuntu 22.04.4 LTS	AArch64 (64-bit)	Kernel version 5.15
Linux Ubuntu 23.10	x86-64 (64-bit)	Kernel version 6.5
Linux Ubuntu 24.10	x86-64 (64-bit)	Kernel version 6.12.1-realtime



NOTE

Power saving modes of the operating systems (StandBy, Sleep, Suspend...) are not supported.

See also: Installing eGrabber on Linux in the Getting Started section of the Coaxlink series or Grablink Duo Handbooks

macOS

eGrabber driver, eGrabber Studio and GenICam Browser (Deprecated) are designed to support all macOS versions from version 12.3.

[Minimum version requirements](#)

macOS 12.3 or higher

[Minimum recommended version](#)

macOS 12.6.3 or higher

[Release validation](#)

This release has been validated with the following version(s):

OS Name & Version	Platform	Notes
macOS 12.6.3	AArch64 (64-bit)	A.k.a. Monterey
macOS 12.7.4	x86-64 (64-bit)	A.k.a. Monterey



NOTE

- The driver for macOS is signed by Euresys using a certificate that has been signed by Apple.
- Power saving modes of the operating systems (StandBy, Sleep, Suspend...) are not supported.

See also: Installing eGrabber on macOS in the Getting Started section of the Coaxlink series or Grablink Duo Handbooks

2.5. Memento

Memento version 4.0 or later is required when using **Coaxlink driver** version 4.0 or later and any version of **eGrabber driver**.

Memento version 9.5 is required to use the **Memento Analyzer**.

2.6. Development Tools

eGrabber driver should be usable with any development tool that supports at least one of these interfaces:

C/C++

eGrabber driver provides four GenICam GenTL producers: `coaxlink.cti`, `grablink.cti`, `gigelink.cti` and `playlink.cti`.

[coaxlink.cti](#)

`coaxlink.cti` supports **Coaxlink frame grabbers**, it includes following libraries:

- An x86_64 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of x86-64 (64-bit) applications.
- An AArch64 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of AArch64 (64-bit) applications.

[grablink.cti](#)

`grablink.cti` supports **[PC1628] Grablink Duo**, it includes following libraries:

- An x86_64 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of x86-64 (64-bit) applications.
- An AArch64 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of AArch64 (64-bit) applications.

[gigelink.cti](#)

`gigelink.cti` supports GigE Vision cameras (including GigE Vision 3.0 cameras that use the GigE Vision RDMA Streaming Protocol), it includes following libraries:

- An x86_64 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of x86-64 (64-bit) applications.
- An AArch64 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of AArch64 (64-bit) applications.

[playlink.cti](#)

`playlink.cti` allows acquiring images recorded in a **Recorder** container as if they were coming from a remote device, it includes following libraries:

- An x86_64 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of x86-64 (64-bit) applications.
- An AArch64 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of AArch64 (64-bit) applications.

eGrabber

eGrabber driver also provides the eGrabber library, a library of C++ classes that provide a high-level interface.

- On Linux, the eGrabber library requires GLIBCXX_3.4.21/CXXABI_1.3.9 → libstdc++.so.6.0.21 or higher.

.NET

- EGrabber.NET assembly for Windows, Linux and macOS (Any CPU) targeting .NET 6.0 (previously called .NET Core)
- EGrabber.NETFramework.dll: a .NET assembly designed to be used with development environments compatible with .NET Framework 4.6 or higher.

NOTE: Updating an application to use EGrabber.NETFramework.dll or EGrabber.NET.dll instead of Coaxlink_NetApi.dll is easy and recommended.

Python

Python bindings for **eGrabber** allow users to call eGrabber functions and operate **eGrabber-driven frame grabbers** from Python scripts. They are compatible with Python 3.8 or higher under Windows, Linux and macOS.

On Windows, the eGrabber installer adds a shortcut in the Windows Start Menu to install the eGrabber Python bindings.

2.7. Software Adapters

eGrabber adapter for Cognex VisionPro



Compatible GenTL producers

- coaxlink.cti
All frame grabbers of the **Coaxlink series** (for CoaXPress and CoaXPress-over-fiber cameras)
- grablink.cti
Grablink Duo frame grabber (for Camera Link cameras)
- gigelink.cti
eGrabber Gigelink (for GigE Vision cameras)

2.8. Software Tools

Software tools delivered together with eGrabber 26.09

Name	Description
eGrabber Gigelink	Free-of-charge library providing a hardware-independent access to GigE Vision cameras (including GigE Vision 3.0 cameras that use the GigE Vision RDMA Streaming Protocol).
eGrabber Recorder	Free-of-charge library that enables image acquisition applications, such as eGrabber -based applications, to write acquired buffers to disk efficiently.
eGrabber Studio	GUI tool for testing the image acquisition with eGrabber from Camera Link, CoaXPress and GigE Vision cameras and upgrading the firmware of eGrabber-driven frame grabbers . StudioLink enables the new Open eVision Studio application to connect to an opened eGrabber Studio EGrabber source, control the acquisition and get images to process within Open eVision Studio .
Firmware Manager Console	Command-line tool for installing or upgrading the firmware embedded in eGrabber-driven frame grabbers .
GenICam Browser (Deprecated)	GUI tool giving access to all the GenApi features exposed by the GenTL Producer(s) in your system.
GenTL Console	Command-line tool giving access to all the functions and commands exposed by the Euresys GenTL Producer.
converter-firmware	Command line tool to perform firmware updates of the [PC3629] Coaxlink CXP-12 to QSFP+ Converter



NOTE

- The **eGrabber driver**, **eGrabber Studio**, **eGrabber Gigelink**, **eGrabber Recorder** and **Playlink**, the **Firmware Manager Console**, the **GenICam Browser (Deprecated)** and the **GenTL Console** can be used free of charge with other Euresys products.
- Starting from release 23.04, **eGrabber Studio** includes a **Firmware Manager**.
- **GenICam Browser** is deprecated and will be removed in a future release. It is still available as **GenICam Browser [Deprecated]** in this release.

2.9. Online Documentation

This release of eGrabber comes with a new edition of the *eGrabber documentation package*.

The package is published to the Internet at the following URL:

https://documentation.euresys.com/Products/eGrabber/eGrabber_26_09/Default.htm

A copy is also published to the Internet at the *Default eGrabber Documentation* URL:

<https://documentation.euresys.com/Products/eGrabber/eGrabber/Default.htm>



TIP

- The first URL (with a version number) gives access to a specific public edition. Its content is permanent.
- The *Default eGrabber Documentation* URL gives access to the latest public edition. Its content is updated every release.

See also: <https://documentation.euresys.com> Euresys Documentation Portal

3. Important Notices

Important notifications to be read before installing and/or using the product on your PC!

3.1. Firmware Revisions	24
3.2. CPU Requirements	24
3.3. Image Buffer Limits	25
3.4. Notice for Linux	25
3.5. Notice for NVIDIA RDMA	25
3.6. Notices for macOS	26
3.7. Notice for Early Coaxlink Drivers	27
3.8. Notice for Coaxlink QSFP28 and Octo CXP-12 users	28

3.1. Firmware Revisions



WARNING

eGrabber driver checks the compatibility of the firmware installed on every frame grabber. For those having an incompatible firmware, the GenTL driver exposes 0 (zero) Device.

If the requirement is not satisfied for all the **eGrabber-driven frame grabbers** in your system, it is *mandatory* to apply the Firmware Upgrade procedure prior to using this version of the driver.



NOTE

Starting with eGrabber 25.03, the firmware revision numbers are listed, for each firmware-variant in the [Firmware Variants table](#)

3.2. CPU Requirements

The image converter requires a CPU that has the Supplemental Streaming SIMD Extension 3 (SSSE3) instruction set.

3.3. Image Buffer Limits

[Maximum buffer size](#)

0xffffffff0 bytes (4 GiB - 16 B) for all operating systems

[Number of buffers](#)

The number of buffers is only limited by available system resources.

NOTE: when using very large numbers of buffers, DSAnnounceBuffer calls can take longer and longer to complete (or even fail with error code GC_ERR_CUSTOM_IOCTL_BUFFER_ANNOUNCE_FAILED). If this happens, the user should set **DmaEngineOptimization=LowMemoryUsage** in the data stream module.

3.4. Notice for Linux

Important notification to be read before installing and/or using the product on your Linux PC

- **Memento** must be installed prior to **eGrabber**.
- If the **eGrabber** package is already installed, proceed as follows:
 - Uninstall **eGrabber**.
 - Install **Memento**.
 - Re-install **eGrabber**.
- If NVIDIA RDMA is required, read ["Notice for NVIDIA RDMA" on page 25](#)

3.5. Notice for NVIDIA RDMA

NVIDIA RDMA is only supported on Linux.

NVIDIA RDMA samples require a NVIDIA GPU that supports RDMA.

The NVIDIA RDMA samples allocate memory on the GPU and announce this memory using NvidiarDmaMemory.

See the following files in the eGrabber sample programs:

- `cpp/egrabber/samples/503-grabn-cuda-rdma-process.*`
- `cpp/nvidia/egrabber-cuda` with the command line argument `cudaRDMA`

[Installation instructions:](#)

- NVIDIA CUDA drivers:

- Follow the installation instructions from: https://developer.nvidia.com/cuda-downloads?target_os=Linux&target_arch=x86_64&Distribution=Ubuntu&target_version=20.04&target_type=deb_network
- NVIDIA driver sources:
 - These are needed to produce the Module.symvers file associated with the installed nvidia driver. This file will be required to install the eGrabber package
 - Select the appropriate driver from <https://www.nvidia.com/download/index.aspx?lang=en-us>
 - Make sure to download the version that matches the nvidia-<version> already installed in /usr/src/
 - Extract the archive with -x option
 - Change to directory kernel in the extracted archive
 - Run make module
 - The file Module.symvers should have been generated
- eGrabber package
 - Extract the egrabber-linux-x86_64 archive
 - Install the package with the following command:
sudo NVIDIA_KERNEL_PATH=<dir path containing Module.symvers> ./install.sh

The line Enabling NVIDIA RDMA build should appear during the installation of the eGrabber package.

A successful build can be confirmed if the command `lsmod | grep coaxlink` (or `lsmod | grep grablink`) indicates that coaxlink (or grablink) module depends on nvidia.

3.6. Notices for macOS

Important notifications to be read before installing the driver on your Mac

Driver types

Install the **Memento** package corresponding to the **eGrabber** driver type:

eGrabber driver package	Memento package
egrabber-macos-aarch64-dext-<MA.MI.RE.BU>.pkg	memento-macos-aarch64-dext-<MA.MI.RE.BU>.pkg
egrabber-macos-x86_64-dext-<MA.MI.RE.BU>.pkg	memento-macos-x86_64-dext-<MA.MI.RE.BU>.pkg



TIP

dext drivers operate in user-mode using the default Full Security policy level.

3.7. Notice for Early Coaxlink Drivers

Several **Coaxlink frame grabbers** underwent a hardware change of the Flash EEPROM control logic.



NOTE

The Flash EEPROM is the memory that stores the contents of the on-board FPGA.

Affected products list

Product	S/N Prefix	First Serial Number of New Cards
[PC1629] Coaxlink Duo PCIe/104-EMB	KDI	10,000
[PC1633] Coaxlink Quad G3	KQG	10,000
[PC1633-LH] Coaxlink Quad G3 LH	KQH	10,000
[PC1635] Coaxlink Quad G3 DF	KDF	10,000
[PC1637] Coaxlink Quad 3D-LLE	KQE	10,000

Consequences

Existing applications using a **Coaxlink driver** prior to version 10.0.0 are required to use a new procedure to install or update the firmware on new boards.

The change has no impact for applications already using **Coaxlink driver 10.0.0** or higher.

With the exception of the firmware update, the change has strictly no impact on the product functionality, performance and specifications:

- The hardware design of these new cards, including the CoaXPress interface, PCI Express interface, the FPGA and the I/O, has not been changed.
- The functionality, performance and specification of the new cards is guaranteed to remain unchanged. Once programmed with the corresponding firmware, the new cards remain compatible with all previous versions of the **Coaxlink driver**.



TIP

For further information, read the *D207EN-Flash EEPROM Change Note* PDF document.

3.8. Notice for Coaxlink QSFP28 and Octo CXP-12 users



WARNING

Firmware update of the [PC3628] Coaxlink QSFP28 and [PC3632] Coaxlink Octo CXP-12 to revision 536 will not permit anymore firmware downgrades below the revision 536!

4. Release Details

4.1. Features Updates 30

4.2. Solved Issues 32

4.3. Changes 33

4.4. Firmware Changes 34

4.5. Breaking Changes 35

4.1. Features Updates

Added and improved features in eGrabber 26.09

eGrabber

- Added new data stream feature StreamScanType
- Added new methods related to buffer parts:
 - Buffer::convertPart
 - Buffer::savePartToDisk
 - Buffer::isGenDC
 - ScopedBuffer::getNumParts
 - ScopedBuffer::getPartInfo
 - ScopedBuffer::convertPart
 - ScopedBuffer::savePartToDisk
 - ScopedBuffer::isGenDC
- **eGrabber** applications and libraries built by **Euresys** are now digitally signed

Frame grabbers

- **Grablink** Added support for new Camera Link Medium, Full, 72-bit and 80-bit tap configurations; the exhaustive list of supported configurations can be found in the [Camera Link Tap Configuration and Tap Geometry Selector documentation page](#)
- **Grablink** Added **CIConfiguration** and **CLTimeSlotsCount** read-only SFNC features to the remote device module
- **Grablink** Added support for new RGB pixel formats:
 - **RGB10, RGB12, RGB14, and RGB16**
 - **RGBa8, RGBa10, RGBa12, RGBa14, and RGBa16**
- **Grablink** Added support for new Camera Link tap geometries:
 - 4-tap: **2X2R_1Y, 4XM_1Y**
 - 5-tap: **1X5_1Y, 5X_1Y**
 - 6-tap: **1X6_1Y, 2X3_1Y, 3X2_1Y, 6X_1Y**
 - 7-tap: **1X7_1Y, 7X_1Y**
 - 8-tap: **2X4E_1Y, 2X4M_1Y, 2X4R_1Y, 4X2M_1Y, 4X2R_1Y, 8XE_1Y, 8XM_1Y**
 - 9-tap: **1X9_1Y, 3X3_1Y, 9X_1Y**
 - 10-tap: **5X2_1Y, 10XE_1Y, 10XM_1Y, 10XR_1Y**
- **Grablink** Added support for Serial Link 460800 and 921600 baud rates
- **Grablink** Added support for the 80-bit 8-tap RGB 10-bit (a.k.a. **DECA_8T30B3**) tap configuration
- **Coaxlink** **Grablink** Ensure "end of" Readout, DMA, and Scan analyzer traces are emitted before their corresponding "start of" traces when events occur simultaneously

eGrabber Studio

- Added "Downscaling mode" options in the advanced setup of the **Buffer pane**; this option controls the downscaling of large images when the zoom level is below 100%; the "Fine" option creates good quality (slower) downscaled images while the "Coarse" option creates lower quality (faster) downscaled images; using downscaled images improves the application reactivity when displaying large images

Coaxlink Converter

- converter-firmware manifest now displays the full device name instead of just its product code

4.2. Solved Issues

Solved issues in eGrabber 26.09

eGrabber

- Fixed an issue that caused `EGrabber::shouldReannounceBuffers()` to incorrectly return false after specific changes in camera settings
- Updated sample `241-multi-part.cpp` to use new buffer part API
- Fixed `Buffer.getPartInfo` to respect GenDC payload size without requiring a prior call to `Buffer.getNumParts`

Frame grabbers

- [Coaxlink](#) Remove irrelevant warning "Unexpected acquisition flags" when `UnpackingMode=Off`
- [Coaxlink](#) [Grablink](#) Now properly fill-in the Year-Month-Day in memento messages reporting the current system date on macOS
- [Grablink](#) Fixed broken images in 80-bit 8-tap/10-bit configuration that occurred for some image widths
- [Grablink](#) Fixed "Unexpected DsizeL=..." Memento warnings when using 10-bit, 12-bit, and 14-bit pixel formats
- [Grablink](#) Fixed "Port handle c: incomplete read at <ADDRESS> (<N> bytes missing)" Memento warnings about `DeviceVendorName` and `DeviceModelName` when using 10-bit, 12-bit, and 14-bit pixel formats
- [Coaxlink](#) [Grablink](#) Fixed an issue where consecutive writes to the EEPROM of the frame grabber would occasionally fail on macOS

eGrabber Studio

- Fixed GenApi Feature visibility handling in [Features Pane](#)

4.3. Changes

Other changes in eGrabber 26.09

Frame grabbers



WARNING

Firmware update of the [PC3628] Coaxlink QSFP28 and [PC3632] Coaxlink Octo CXP-12 to revision 536 will not permit anymore firmware downgrades below the revision 536!

- **Coaxlink** If CxpControlParameter[KeepInvalidXmlUrls]=0 (the default) and the first character of the first XML URL read from the camera is \xff, the CoaXPress device discovery fails (and is executed again from the beginning)

NOTE: In eGrabber 26.07 and 26.08, if CxpControlParameter[KeepInvalidXmlUrls]=0 (the default), and if the XML URL is incorrect (e.g., it is empty, or it contains trailing characters), the CoaXPress device discovery fails (and is executed again from the beginning)

- **Coaxlink** **Grablink** Lowered "DMA backend is not idle" Memento warning to debug level

eGrabber Recorder

- **eGrabber Recorder** and **Playlink** no longer require a license

4.4. Firmware Changes

Firmware revision 533

Applies to	Description
[PC1628] Grablink Duo (all firmware variants)	Added support for Serial Link 460800 and 921600 baud rates

4.5. Breaking Changes

Changes in the API that are not backward compatible

Since eGrabber 26.04

- **Python** Changed the return type of the following functions:
 - `EGrabber.gc_read_port` returns bytearray instead of `ctypes.c_char_Array_N`
 - `RemoteDeviceData.data` returns bytes instead of `ctypes.c_ubyte_Array_1012`
 - `Buffer.get_pixels` returns bytearray instead of `ctypes.c_ubyte_Array_N`
 - `Buffer.pixels` returns bytearray instead of `ctypes.c_ubyte_Array_N`
 - `ConvertedBuffer.pixels` returns bytearray instead of `ctypes.c_char_Array_N`
 - `Recorder.read` returns bytearray instead of `ctypes.c_char_Array_N`
- **Recorder** The value of `BUFFER_INFO_CUSTOM_ALLOCATED_SIZE` is now the recommended value for the field size of the `RECORDER_BUFFER_INFO` struct when writing to a Recorder container (see samples). Using the previously recommended value, `BUFFER_INFO_SIZE`, can lead to performance degradation due to extra copies done to meet alignment constraints of Recorder

Since eGrabber 26.01

Moved built-in scripts `egrabber://save-state.js` and `egrabber://restore-state.js` into `egrabber://deprecated/`

Since eGrabber 25.09

- On Windows, `coaxlink.cti`, `grablink.cti`, `gigelink.cti`, and `playlink.cti` now look for their configuration files (`coaxlink.ini`, `grablink.ini`, `gigelink.ini`, and `playlink.cfg` respectively) in `%PUBLIC%\Documents\Euresys\eGrabber\` instead of `%PUBLIC%\Documents\eGrabber\`
- Removed 2 member variables from `NewBufferData`; these member variables are for internal use only and should not be used:
 - **Python** `NewBufferData.dsh` and `NewBufferData.bh`
 - **.NET** `NewBufferData::DataStreamHandle` and `NewBufferData::BufferHandle`

Since eGrabber 25.07

Removed `BUFFER_INFO_CUSTOM_STREAM_LINE_WIDTH`, `BUFFER_INFO_CUSTOM_STREAM_LINE_PITCH`, `BUFFER_INFO_CUSTOM_STREAM_STRIPE_HEIGHT`, `BUFFER_INFO_CUSTOM_STREAM_STRIPE_PITCH`, `BUFFER_INFO_CUSTOM_STREAM_STRIPE_OFFSET`, and `BUFFER_INFO_CUSTOM_STREAM_BLOCK_HEIGHT`, which were deprecated since eGrabber 24.09

**WARNING**

- `BUFFER_INFO_CUSTOM_STREAM_STRIPE_ARRANGEMENT` is deprecated and will be removed in a future release
- `StripeArrangement=Geometry_1X_1YE` is deprecated and will be removed in a future release; `StripeArrangement=Geometry_1X_1Y` with `ReverseY=True` should be used instead

Since eGrabber 25.04

- **.NET** Fixed a typo in `EGrabberDiscovery`; the property `GentTL` has been renamed to `GenTL`; an application using `EGrabberDiscovery.GentTL` will no longer work starting from this release of eGrabber unless it's updated to use `EGrabberDiscovery.GenTL` instead
- Deprecation of `EGrabbers.h` is now enforced; `EGrabbers.h` was deprecated in **eGrabber 22.03**; two options to fix user code:
 - **recommended change** use `EGrabberDiscovery` instead of `EGrabbers`
 - add `#define EURESYS_USE_EGRABBERS_DEPRECATED_API` before `#include <EGrabbers.h>`

Since eGrabber 24.09

- **.NET** Improved `EGrabber.NET` API to support buffers larger than 2GiB

Since eGrabber 24.06

cti configuration files locations

- `coaxlink.cti`, `grablink.cti`, and `gigelink.cti` now look for their configuration file (`coaxlink.ini`, `grablink.ini`, and `gigelink.ini`, respectively) in the eGrabber configuration directory:
 - on Windows: `%PUBLIC%\Documents\Euresys\eGrabber\`
 - on Linux: `/etc/opt/euresys/egrabber/`
 - on macOS: `/usr/local/etc/opt/euresys/egrabber/`

Since eGrabber 22.08

eGrabber Recorder : Removed asynchronous writes

- The eGrabber Recorder binary interface has not changed, however the arguments related to `async handles` are no longer functional; applications using this API need to be adapted (depending on the application architecture, a dedicated thread will be required to perform the writes in the background).
- The Recorder Python bindings have been adapted to remove the asynchronous writes as well as the `Record flags` (e.g. `recorder.read()` now returns a tuple with 2 elements instead of 3).

Since eGrabber 22.05

- Previously, `enableEvent<NewBufferData>` was implicitly performed in the constructor of `EGrabber`.
- Now, `enableEvent<NewBufferData>` is performed in `start` unless `NewBufferData` event has been disabled beforehand; any attempt to pop a `NewBufferData` structure before `start` and without explicitly enabling `NewBufferData` event will lead to an error.

Since eGrabber 19.0

The minimal GLIBC version required for x86-64 (64-bit) Linux binaries is now 2.14.

Since eGrabber 14.0

- `BUFFER_INFO_SIZE_FILLED` now reports the number of bytes transferred, excluding padding (if any)
- `BUFFER_INFO_DATA_SIZE` reports the value that was previously reported by `BUFFER_INFO_SIZE_FILLED`

Since Coaxlink 12.2

`NeverWrite` is the new default value of `CxpLinkConfigurationOption`.

NOTE: The recommended way to set the CoaXPress link configuration is by using the equivalent feature in the remote device module; this can be named `ConnectionConfig`, `LinkConfig`, or `CxpLinkConfiguration` depending on the camera.

NOTE: Alternatively, the previous behavior can be restored by setting `CxpLinkConfigurationOption` to `AlwaysWrite`. However, the GenApi cache for this register might become invalid!

Since Coaxlink 12.0

- **[PC1637] Coaxlink Quad 3D-LLE:** `STREAM_INFO_CUSTOM_WIDTH` and `BUFFER_INFO_WIDTH` are now multiplied by two if two laser-lines are extracted
- The Coaxlink .NET assembly targets:
 - the .NET framework 2.0 in Coaxlink versions up to 11.x
 - the .NET framework 4.0 in Coaxlink versions 12.0 and higher

Since Coaxlink 11.1

Behavior of [PC1637] Coaxlink Quad 3D-LLE from firmware revision 285:

- The line pitch alignment has been changed to 16 bytes (before firmware revision 285, the line pitch alignment of the card was 8 bytes); this means the Width of the camera must be a multiple of 16 (Mono8).
- When the extraction is disabled, the card behaves like an area-scan variant (and the data stream feature **BufferHeight** is not available); when the extraction is enabled, **BufferHeight** is available and determines the number of profiles to extract; when the extraction is disabled, applications no longer require extra care to make sure acquisitions always start with the first line of the acquired images.

CoaXPress

Ignore any remote device whose master connection is not connected to the first connector of a Coaxlink Device; the driver now requires a master connection to be connected to the first connector whereas the extension connections can be connected to the remaining Coaxlink Device connectors in any order.

See also: "Firmware Variants" on page 9 for the applicable connection schemes.

Image converter

Updated ImageConvertInput and ImageConvertOutput structures.
Subsequent potential build issues can be fixed by either:

- using IMAGE_CONVERT_INPUT and IMAGE_CONVERT_OUTPUT initialization macros (recommended approach) or
- adding the suffix Version0 to ImageConvertInput and ImageConvertOutput types.

NOTE: Users of EGrabber are not affected by this breaking change

Since Coaxlink 10.3

PayloadSize behavior: The feature PayloadSize is not available anymore when the remote device Width is not in line with the data stream Width.Inc

Since Coaxlink 10.2

Additional constructor parameter required: The grabber classes (based on EGrabber) instantiated by EGrabbers require the additional constructor parameter (bool remoteRequired).

See also: sample "213-egrabbers" for details

Since Coaxlink 10

Deprecated the functions `Features`, `RegexFeatures`, `GlobFeatures`, `EnumEntries`, `RegexEnumEntries`, `GlobEnumEntries` from namespace `Euresys`, which are still available by #defining `EURESYS_USE_NS_EURESYS_DEPRECATED_API`. Two options to fix user code:

1. Recommended change Replace all occurrences of:

- `Euresys::Features()` by `Euresys::query::features()`
- `Euresys::RegexFeatures(re)` by `Euresys::query::features().regex(re)`
- `Euresys::GlobFeatures(g)` by `Euresys::query::features().glob(g)`
- `Euresys::EnumEntries(f)` by `Euresys::query::enumEntries(f)`
- `Euresys::RegexEnumEntries(f, re)` by `Euresys::query::enumEntries(f).regex(re)`
- `Euresys::GlobEnumEntries(f, g)` by `Euresys::query::enumEntries(f).glob(g)`

2. Or add `#define EURESYS_USE_NS_EURESYS_DEPRECATED_API` before `#include <EGrabber.h>` (or `#include <EGenTL.h>`), a quick fix that doesn't require changing source code.

Since Coaxlink 9.3.1

Removed data stream event counts from the list of possible contexts of device event notifications: `StartOfCameraReadoutEventCount`, `EndOfCameraReadoutEventCount`, `StartOfScanEventCount`, `EndOfScanEventCount`, `RejectedFrameEventCount`, and `RejectedScanEventCount` are no longer valid values for `EventNotificationContext1`, `EventNotificationContext2`, and `EventNotificationContext3` in the device module.

Since Coaxlink 9.3

Data stream features `StartOfScanTriggerSource`, `EndOfScanTriggerSource` and `ScanLength` are now reset by the data stream feature `StreamReset`. Previously, they were reset by the device feature `DeviceReset`.

Since Coaxlink 9.2

GenApi Features Range Checking

Range checking will prevent applications from setting forbidden values to camera features. A meaningful error will be reported if such an event should happen.

Since Coaxlink 9.1.1

Camera Model - Exposure Time Range Boundaries

When `ExposureTimeMin` and/or `ExposureTimeMax` are/is set, the order in which the features `ExposureTimeMin`, `ExposureTimeMax` and `ExposureTime` are set is imposed by the constraints.

Since Coaxlink 7.1.1

[GenTL 1.5 header file](#)

Moved to standard GenTL 1.5 header file (was previously GenTL 1.4):

- GenTL 1.5 changed namespace from `GenICam::Client` to `GenTL`,
- Coaxlink custom GenTL definitions have been moved accordingly from the namespace `GenICam::Client::Euresys` to namespace `GenTL::EuresysCustomGenTL`,
- replaced header file `GenTL_v1_4.h` by `GenTL_v1_5.h`,
- replaced header file `GenTL_v1_4_EuresysCustom.h` by `GenTL_v1_5_EuresysCustom.h`.

[Euresys::GenTL class renaming](#)

Renamed the class `Euresys::GenTL` into `Euresys::EGenTL` to avoid name conflicts with the new standard GenTL 1.5 namespace `GenTL`. This will impact any code using the class `Euresys::GenTL`:

- renamed header file `EuresysGenTL.h` into `EGenTL.h`,
- renamed header file `EuresysGenTLErrors.h` into `EGenTLErrors.h`,
- `Euresys::EGenTL` is now declared in header file `EGenTL.h`.

[Deprecated Euresys::SharedGenTL Class](#)

Deprecated the class `Euresys::SharedGenTL`, which is still available by defining `EURESYS_USE_SHAREDGENTL_DEPRECATED_API`.

Two options to fix user code:

1. *Recommended change* Replace all occurrences of `Euresys::SharedGenTL` by `Euresys::EGenTL`,
2. Or add `#define EURESYS_USE_SHAREDGENTL_DEPRECATED_API` before `#include <EGrabber.h>`, a quick fix that doesn't require changing source code.

[GenTL 1.5 Changes](#)

Announcing or revoking buffers while acquiring returns the error code `GC_ERR_BUSY` (was `GC_ERR_RESOURCE_IN_USE` for GenTL 1.4)

Revoking a queued buffer returns the error code `GC_ERR_BUSY` (was `GC_ERR_RESOURCE_IN_USE` for GenTL 1.4)

New device access status values (defined by GenTL 1.5) returned by the GenTL functions `IFGetDeviceInfo` and `DevGetInfo` for the command `DEVICE_INFO_ACCESS_STATUS`:

- `DEVICE_ACCESS_STATUS_OPEN_READWRITE`: when the device is opened by the current producer with read/write access
- `DEVICE_ACCESS_STATUS_OPEN_READONLY`: when the device is opened by the current producer with read-only access

Since Coaxlink 7.0.0

Product Rename

Renamed **Coaxlink Duo PCIe/104** into **Coaxlink Duo PCIe/104-MIL**; this will impact the names of GenTL interfaces (i.e., `INTERFACE_INFO_ID`)

OemSafetyKey Length

The length of **ProgramOemSafetyKey** and **CheckOemSafetyKey** is now limited by a user-configurable **MaximumOemKeyLength** (4096 characters by default)

LUT Configuration Locking

LUT configuration features (datastream) are locked while grabbing.

CIC Features Availability

Features related to the CIC (device) are not available when **CameraControlMethod** is **NC** or **EXTERNAL**.

Since Coaxlink 4.6.1

EGrabber API

Deprecated EGrabber method `announceBuffer` (superseded by `announceAndQueue`).

Two options to fix user code:

1. *Recommended change* Replace all occurrences of `announceBuffer` by `announceAndQueue` (`GenTLMemory(...)`) or `announceAndQueue(UserMemory(...)`),
2. Or add `#define EURESYS_USE_EGRABBER_DEPRECATED_API` before `#include <EGrabber.h>`.

Since Coaxlink 4.5.1

Euresys Name Space for EGrabber Classes

EGrabber C++ classes now belong to Euresys namespace.

Two options to fix user code:

1. *Recommended change* Replace each occurrence of `EGrabber` by `Euresys::EGrabber`,
2. Or add `using namespace Euresys;` after `#include <EGrabber.h>`.

Since Coaxlink 4.4.1

EGrabber API

The API of EGrabber .NET classes have changed since Coaxlink 4.4.0 beta. GenTL class now behaves like SharedGenTL, which is what most users need

NOTE: The GenTL constructor accepts a new argument, named `shared`, which can be used to revert to the old behavior.

RGBConverter.h

Added `inplace1x2yeReordering` methods instead of `Inplace1x2yeReordering` class

NOTE: User code needs to be adapted to call `inplace1x2yeReordering` instead of creating an `Inplace1x2yeReordering` instance, please see `include/RGBConverter.h` for a code sample.

Since Coaxlink 4.4.0

.NET Assembly

Added new assembly exposing EGrabber classes, previous CoaxlinkGrabber classes are removed from the assembly.

EGrabber

Deprecated `getInfoString` methods (replaced by `getInfo`).

Two options to fix user code:

1. *Recommended change* Replace all occurrences of `getInfoString<module>` (and `getBufferInfoString`) by `getInfo<module, std::string>` (and `getBufferInfo<std::string>`)
2. Or add `#define EURESYS_USE_EGRABBER_DEPRECATED_API` before `#include <EGrabber.h>`.

GenTL C++ class

Deprecated `bayerConvert` function

Though the function `bayerConvert` is superseded by the image converter, it is still possible to use it, if required please add `#define EURESYS_USE_BAYER_DEPRECATED_API` before `#include <EuresysGenTL.h>` or `#include <EGrabber.h>`

Since Coaxlink 4.3

Data Stream Module GenApi feature

`UnpackingMode`: Changed default value to LSB (instead of MSB)

Since Coaxlink 4.1

Device Module features changes

- Merged `CycleTriggerSource` and `CycleHardwareTriggerSource` features.
- Renamed `CycleSoftwareTrigger` into `StartCycle`.
- Renamed `CyclePeriodTarget` into `CycleMinimumPeriod`.
- Renamed `ErrorCounter` into `ErrorCount`.
- Renamed `ErrorCounterReset` into `ErrorCountReset`.
- Removed backward compatibility for deprecated features: `TriggerSource`, `TargetFramePeriod`, `ExposureRecovery`.

5. Known Issues

Known issues of eGrabber 26.09

5.1. [PC1628] Grablink Duo Limitations 45

5.2. Deviations from the GenTL Specification 46

5.3. Deviations from the PCI Express Specification 48

5.4. GenICam Browser (Deprecated) and gentl view Limitations 48

5.1. [PC1628] Grablink Duo Limitations

Unsupported device types and unavailable features of [PC1628] Grablink Duo in eGrabber 26.09

Applies to:

Duo

Unsupported device types

[Cameras with specific sensor geometries](#)

- Bayer CFA bilinear color line-scan cameras

[Cameras with specific Camera Link requirements](#)

- Camera Link Lite configuration
- Skipping Camera Link clocks at begin-of-line
- Skipping LVAL lines at begin-of-frame

[Cameras with specific tap configurations and geometries](#)

- All geometries with more than 1-tap along the Y-direction (*_1Y2, *_1Y3 and *_2YE)

Unavailable features

[Pixel processing](#)

- White Balance Operator

[Image processing](#)

- Horizontal image flipping
- Image cropping

[Other features](#)

- Connect Camera Link enable signals of Channel Links Y and Z as general-purpose inputs
- C2C Synchronization QDC forwarding

5.2. Deviations from the GenTL Specification

EventKill

GenTL specification

The GenTL specification states that:

- In case of multiple pending wait operations EventKill causes one wait operation to return with a GC_ERR_ABORT error code.
- This means that if more than one thread waits for an event, the EventKill function terminates only one wait operation and other threads will continue execution.
- Therefore in order to cancel all pending wait operations EventKill must be called as many times as wait operations are pending.
- In case this function is called while no wait operation was pending the next call to EventGetData will return a GC_ERR_ABORT.



NOTE

- This implementation is prone to race conditions: calling EventKill N times in a row to kill exactly N waiting threads is not guaranteed to work as expected because signaling an event that is already in the signaled state has no effect. In other words, some of the EventKill calls could have no effect.
- EventKill as specified is not easy to use: How many EventKill calls are required? How many EventGetData calls should we expect to return GC_ERR_ABORT? Note that race conditions affect these questions.

Euresys GenTL implementation

The Euresys GenTL implementation solves these issues, but differs slightly:

- EventKill aborts all pending wait operations on the event handle.
- EventKill has no impact on subsequent wait operations.

DSStopAcquisition

GenTL specification

The GenTL specification states that:

- Each call to DSStartAcquisition must be accompanied by a call to DSStopAcquisition.
- Argument iNumToAcquire passed to DSStartAcquisition sets the number of filled delivered buffers after which the acquisition engine stops automatically.
- There must be a call to DSStopAcquisition accompanying each call to DSStartAcquisition even though the stream already stopped because the number of frames to acquire was reached.
- DSStopAcquisition returns GC_ERR_RESOURCE_IN_USE when the acquisition engine has already been terminated or has not been started.

Euresys GenTL implementation

The Euresys GenTL implementation differs slightly:

- DSStopAcquisition will not return GC_ERR_RESOURCE_IN_USE if the data stream hasn't been started.
- DSStopAcquisition will not return GC_ERR_RESOURCE_IN_USE if the data stream has already been stopped by a prior call to DSStopAcquisition.
- DSStopAcquisition will not return GC_ERR_RESOURCE_IN_USE if the data stream has stopped automatically after iNumToAcquire images have been captured.

In other words, DSStopAcquisition is idempotent: it can be applied multiple times without changing the result beyond the initial application.

With the Euresys implementation, it is not necessary to treat some errors as normal, and race conditions (between DSStopAcquisition and the automatic stop of the data stream) are avoided. Furthermore, if the data stream has stopped automatically after acquiring iNumToAcquire images, DSStartAcquisition can be called without first calling DSStopAcquisition.

5.3. Deviations from the PCI Express Specification

Applies to:

[PC1633] Coaxlink Quad G3, [PC1633-LH] Coaxlink Quad G3 LH and [PC1635] Coaxlink Quad G3 DF.

QuadG3

QuadG3LH

QuadG3DF ^{EOL}

[PC1633] Coaxlink Quad G3, [PC1633-LH] Coaxlink Quad G3 LH and [PC1635] Coaxlink Quad G3 DF operate only at PCIe 2.0 and PCIe 3.0 link speeds.

These products cannot be used when inserted in PCIe revision 1.x slots.

Applies to:

[PC3628] Coaxlink QSFP28.

QSFP28

[PC3628] Coaxlink QSFP28 operates only at PCIe 4.0 link speeds.

This product is not compatible with PCIe slots using revisions 1.x, 2.x, and 3.x.

NOTE: The support for PCIe 3.0 will be included in a future release.

5.4. GenlCam Browser (Deprecated) and gentl view Limitations

Only images having a width aligned on a 4-bytes boundary can be displayed correctly.

6. Appendix

6.1. Firmware Variants History

History of officially supported firmware variants by eGrabber and Coaxlink drivers.

Content description

Each section, is dedicated to a [firmware set](#)¹. It is entitled with the name of the target products group e.g. PC1633 - Coaxlink Quad G3

The first table shows the **list of products** sharing the same firmware set:

- The *Product* column shows the product name, e.g. [PC1633] Coaxlink Quad G3 and [PC1633-LH] Coaxlink Quad G3 LH
- The *First release* column shows the version of the first driver release officially supporting this product.
- The *Last release* column shows, when applicable, the version of the last driver release supporting this product.
- The *Notes* column gives additional information

The second table shows all the firmware variants belonging to the firmware set:

- The *Firmware variant* column shows the [firmware variant](#)² name.
- The *First release* column shows the version of the first driver release officially supporting this firmware variant.
- The *Last release* column shows, when applicable, the version of the last driver release supporting this firmware variant.
- The *Notes* column gives additional information.

¹A collection of firmware gathering all the variants for the same Target Product(s group). A firmware set is named as follows: PC<ProductCode> - <ProductName>. When several products share a common firmware, the reference of the product without product code suffix is used! For instance , the PC1633 - Coaxlink Quad G3 target product(s group) refers to two products: [PC1633] Coaxlink Quad G3 and [PC1633-LH] Coaxlink Quad G3 LH.

²A firmware instance providing a specific set of features. A firmware variant is named after the main feature. E.g.: the "1-camera, linescan" variant allows the target product(s) to connect 1 line-scan camera.

PC1628 - Grablink Duo firmware set

Applies to:

Product	First release	Last release	Notes
[PC1628] Grablink Duo	eGrabber 23.02		
Firmware Variant	First release	Last release	Notes
1-camera	eGrabber 23.02		
1-camera, line-scan	eGrabber 23.02		
2-camera	eGrabber 23.02		
2-camera, line-scan	eGrabber 23.02		

PC1629 - Coaxlink Duo PCIe/104-EMB firmware set

Applies to:

Product	First release	Last release	Notes
[PC1629] Coaxlink Duo PCIe/104-EMB	Coaxlink 6.0		End-of-life product
Firmware Variant	First release	Last release	Notes
1-camera	Coaxlink 6.0		
1-camera, line-scan	Coaxlink 6.0		
2-camera	Coaxlink 6.0		

PC1630 - Coaxlink Mono firmware set

Applies to:

Product	First release	Last release	Notes
[PC1630] Coaxlink Mono	Coaxlink 2.0		End-of-life product
Firmware Variant	First release	Last release	Notes
1-camera	Coaxlink 2.0		

PC1631 - Coaxlink Duo firmware set

Applies to:

Product	First release	Last release	Notes
[PC1631] Coaxlink Duo	Coaxlink 2.0		End-of-life product
Firmware Variant	First release	Last release	Notes
1-camera	Coaxlink 2.0		
1-camera, line-scan	Coaxlink 9.1		
2-camera	Coaxlink 3.2		
2-camera, line-scan	Coaxlink 9.1		

PC1632 - Coaxlink Quad firmware set

Applies to:

Product	First release	Last release	Notes
[PC1632] Coaxlink Quad	Coaxlink 1.0		End-of-life product

Firmware Variant	First release	Last release	Notes
1-camera	Coaxlink 1.0		
1-camera, line-scan	Coaxlink 4.1		
2-camera	Coaxlink 4.2		

PC1633 - Coaxlink Quad G3 firmware set

Applies to:

Product	First release	Last release	Notes
[PC1633] Coaxlink Quad G3	Coaxlink 4.0		
[PC1633-LH] Coaxlink Quad G3 LH	Coaxlink 11.1		

Firmware Variant	First release	Last release	Notes
1-camera	Coaxlink 4.0		
1-camera, 4-data-stream	Coaxlink 9.3		
1-camera, line-scan	Coaxlink 4.1		
1-slm-camera	Coaxlink 6.1	eGrabber 24.12	Retired firmware variant
1-sls-camera	Coaxlink 6.1	eGrabber 24.12	Retired firmware variant
2-camera	Coaxlink 4.2		
2-camera, bayer	eGrabber 22.1		
2-camera, line-scan	Coaxlink 4.3		
3-camera	Coaxlink 11.2		
4-camera	Coaxlink 4.0		
4-camera, line-scan	Coaxlink 7.1		

PC1634 - Coaxlink Duo PCIe/104-MIL firmware set

Applies to:

Product	First release	Last release	Notes
[PC1634] Coaxlink Duo PCIe/104-MIL	Coaxlink 6.0		End-of-life product
Firmware Variant	First release	Last release	Notes
1-camera	Coaxlink 6.0		
1-camera, line-scan	Coaxlink 6.0		
2-camera	Coaxlink 6.0		

PC1635 - Coaxlink Quad G3 DF firmware set

Applies to:

Product	First release	Last release	Notes
[PC1635] Coaxlink Quad G3 DF	Coaxlink 5.0		End-of-life product
Firmware Variant	First release	Last release	Notes
1-camera	Coaxlink 5.0		
1-df-camera	Coaxlink 5.0		
1-camera, line-scan	Coaxlink 5.0		
1-df-camera, line-scan	Coaxlink 5.0		

PC1637 - Coaxlink Quad 3D-LLE firmware set

Applies to:

Product	First release	Last release	Notes
[PC1637] Coaxlink Quad 3D-LLE	Coaxlink 9.0		
Firmware Variant	First release	Last release	Notes
1-camera	Coaxlink 9.0		
2-camera	eGrabber 24.07		

PC1638 - Coaxlink Quad CXP-3 firmware set

Applies to:

Product	First release	Last release	Notes
[PC1638] Coaxlink Quad CXP-3	Coaxlink 8.0	Coaxlink 10.5	Retired product
Firmware Variant	First release	Last release	Notes
4-camera	Coaxlink 8.0	Coaxlink 10.5	Retired product

PC1640 - Coaxlink Quad G3 T firmware set

Applies to:

Product	First release	Last release	Notes
PC1640 Coaxlink Quad G3 T			Retired custom product

Firmware Variant	First release	Last release	Notes
4-camera			Retired custom product

PC3602 - Coaxlink Octo firmware set

Applies to:

Product	First release	Last release	Notes
[PC3602] Coaxlink Octo	Coaxlink 10.0		

Firmware Variant	First release	Last release	Notes
1-camera	Coaxlink 10.1		
1-camera, line-scan	Coaxlink 10.1		
2-camera	Coaxlink 10.0		
2-camera, line-scan	Coaxlink 10.1		
3-camera	Coaxlink 12.7		
4-camera	Coaxlink 10.2		
4-camera, line-scan	Coaxlink 10.5		
5-camera	Coaxlink 10.2		
5-camera, 5D22211	eGrabber 16.1		
6-camera	eGrabber 26.06		
8-camera	Coaxlink 10.0		
8-camera, line-scan	eGrabber 24.12		

PC3603 - Coaxlink Quad CXP-12 firmware set

Applies to:

Product	First release	Last release	Notes
[PC3603] Coaxlink Quad CXP-12	Coaxlink 10.4		End-of-life product
[PC3603-4] Coaxlink Quad CXP-12	eGrabber 15.0		

Firmware Variant	First release	Last release	Notes
1-camera	Coaxlink 10.4		
1-camera, line-scan	Coaxlink 11.0		
2-camera	Coaxlink 12.5		
2-camera, line-scan	eGrabber 22.1		
3-camera	eGrabber 25.04		
3-camera, line-scan	eGrabber 25.12		
4-camera	Coaxlink 10.4		
4-camera, line-scan	eGrabber 23.08		

PC3620 - Coaxlink Quad CXP-12 JPEG firmware set

Applies to:

Product	First release	Last release	Notes
[PC3620] Coaxlink Quad CXP-12 JPEG	Coaxlink 11.0	eGrabber 25.12	Retired product
[PC3620-4] Coaxlink Quad CXP-12 JPEG	eGrabber 15.0	eGrabber 25.12	Retired product

Firmware Variant	First release	Last release	Notes
4-camera	Coaxlink 11.0	eGrabber 25.12	Retired product

PC3621 - Coaxlink Mono CXP-12 firmware set

Applies to:

Product	First release	Last release	Notes
[PC3621] Coaxlink Mono CXP-12	Coaxlink 12.4		
[PC3621-LH] Coaxlink Mono CXP-12 LH	Coaxlink 12.4		

Firmware Variant	First release	Last release	Notes
1-camera	Coaxlink 12.4		
1-camera, line-scan	eGrabber 19.0		

PC3622 - Coaxlink Duo CXP-12 firmware set

Applies to:

Product	First release	Last release	Notes
[PC3622] Coaxlink Duo CXP-12	Coaxlink 12.4		
[PC3622-LH] Coaxlink Duo CXP-12 LH	Coaxlink 12.4		

Firmware Variant	First release	Last release	Notes
1-camera	Coaxlink 12.4		
1-camera, line-scan	eGrabber 18.0		
2-camera	Coaxlink 12.4		
2-camera, line-scan	eGrabber 19.0		

PC3623 - Coaxlink Quad CXP-12 Value firmware set

Applies to:

Product	First release	Last release	Notes
[PC3623] Coaxlink Quad CXP-12 Value	eGrabber 23.08		

Firmware Variant	First release	Last release	Notes
1-camera	eGrabber 23.08		
1-camera, line-scan	eGrabber 23.08		
2-camera	eGrabber 23.08		
2-camera, line-scan	eGrabber 23.08		
3-camera	eGrabber 25.07		
4-camera	eGrabber 23.08		
4-camera, line-scan	eGrabber 23.08		

PC3624 - Coaxlink Quad CXP-12 DF firmware set

Applies to:

Product	First release	Last release	Notes
[PC3624] Coaxlink Quad CXP-12 DF	eGrabber 24.03		

Firmware Variant	First release	Last release	Notes
1-camera	eGrabber 24.03		
1-df-camera	eGrabber 24.03		
1-camera, line-scan	eGrabber 24.03		
1-df-camera, line-scan	eGrabber 24.03		

PC3625 - Coaxlink QSFP+ firmware set

Applies to:

Product	First release	Last release	Notes
[PC3625] Coaxlink QSFP+	eGrabber 17.0		

Firmware Variant	First release	Last release	Notes
1-camera	eGrabber 17.0		
1-camera, line-scan	eGrabber 21.0		
2-camera	eGrabber 25.10		
4-camera	eGrabber 25.02		
4-camera, line-scan	eGrabber 26.02		

PC3628 - Coaxlink QSFP28 firmware set

Applies to:

Product	First release	Last release	Notes
[PC3628] Coaxlink QSFP28	eGrabber 25.10		

Firmware Variant	First release	Last release	Notes
1-camera	eGrabber 25.10		
1-camera, line-scan	eGrabber 25.10		

PC3629 - Coaxlink CXP-12 to QSFP+ Converter firmware set

Applies to:

Product	First release	Last release	Notes
[PC3629] Coaxlink CXP-12 to QSFP+ Converter	eGrabber 24.10		

Firmware Variant	First release	Last release	Notes
1xCxp2CoFx4	eGrabber 24.10		
2xCxp2CoFx2	eGrabber 25.10		
4xCxp2CoFx1	eGrabber 25.10		

PC3633 - Coaxlink Quad CXP-12 3D-LLE firmware set

Applies to:

Product	First release	Last release	Notes
[PC3633] Coaxlink Quad CXP-12 3D-LLE	eGrabber 24.12		

Firmware Variant	First release	Last release	Notes
1-camera	eGrabber 24.12		

6.2. Operating Systems History

History of supported operating systems by **eGrabber** and **Coaxlink** drivers.

About this table

- The *OS* column shows the Operating System name, possibly suffixed by its version number.
- The *PA* column shows the Processor Architecture.
- The *First release* column shows the name of the first eGrabber (or Coaxlink driver) supporting this OS/PA combination.
- The *Last release* column shows, when available, the name of the last eGrabber (or Coaxlink driver) supporting this OS/PA combination.
- The *Notes* column gives additional information about this OS/PA combination

OS	PA	First release	Last release	Notes
Windows 7 SP1	x86 (32-bit)	Coaxlink 1.0	eGrabber 21.0	
Windows 7 SP1	x86-64 (64-bit)	Coaxlink 1.0	eGrabber 24.12	Includes Windows Server 2008 R2
Windows 8	x86 (32-bit)	Coaxlink 1.0	Coaxlink 9.4	
Windows 8	x86-64 (64-bit)	Coaxlink 1.0	Coaxlink 9.4	
Windows 8.1	x86 (32-bit)	Coaxlink 4.5	eGrabber 21.0	
Windows 8.1	x86-64 (64-bit)	Coaxlink 4.5	eGrabber 24.12	Includes Windows Server 2012 R2
Windows 10	x86 (32-bit)	Coaxlink 4.5	eGrabber 21.0	
Windows 10	x86-64 (64-bit)	Coaxlink 4.5	eGrabber 25.12	Versions < 1809
Windows 10	x86-64 (64-bit)	Coaxlink 4.5		
Windows 11	x86-64 (64-bit)	eGrabber 22.03		
Linux	x86 (32-bit)	Coaxlink 3.0	eGrabber 17.0	
Linux	x86-64 (64-bit)	Coaxlink 3.0	eGrabber 25.12	Linux kernels < v4.4; GLIBC < 2.23
Linux	AArch64 (64-bit)	Coaxlink 7.0	eGrabber 25.12	Linux kernels < v4.4; GLIBC < 2.23
Linux	x86-64 (64-bit)	Coaxlink 3.0		
Linux	AArch64 (64-bit)	Coaxlink 7.0		
macOS 10.12	x86-64 (64-bit)	Coaxlink 10.0	eGrabber 22.12	(kext drivers) A.k.a. Sierra
macOS 10.13	x86-64 (64-bit)	Coaxlink 10.0	eGrabber 22.12	(kext drivers) A.k.a. High Sierra
macOS 12.3	AArch64 (64-bit)	eGrabber 22.08		Studio added in 23.04
macOS	AArch64 (64-bit)	eGrabber 22.08	eGrabber 25.12	kext drivers
macOS	x86-64 (64-bit)	eGrabber 22.08	eGrabber 25.12	kext drivers
macOS	AArch64 (64-bit)	eGrabber 23.04		dext drivers using Driver Kit extension
macOS	x86-64 (64-bit)	eGrabber 25.09		dext drivers using Driver Kit extension

NOTE: Linux OS: Gigalink and Recorder were added in eGrabber 22.08

6.3. About Icons


Icons are used everywhere in the eGrabber documentation to represent a specific product. They are particularly useful in "Applies to" elements to obtain a compact representation of a product list.

Applies to:

Duo	Duo104EMB ^{EOL}	Mono ^{EOL}	Duo ^{EOL}	Quad ^{EOL}	QuadG3	QuadG3LH
QuadG3DF ^{EOL}	Quad3DLLE	Octo	Quad1Z ^{EOL}	Quad12-4	Mono1Z ^{REQ}	Mono12LH
Duo12	Duo12LH ^{REQ}	Value12	Quad12DF	QSFP+	QSFP28	QSFP+Conv
Quad12LLE	1625	1676	1636	3300 ^{EOL}	3301 ^{EOL}	3302 ^{EOL}
3303	3304	3610 ^{EOL}	3612 ^{EOL}	3613	3614	3618
Gigalink	Recorder	Studio	Memento	eGrabber		

Icons used in this edition of the eGrabber documentation

Icons are composed of graphical elements characterizing the product:

Background	Description
	Analog product (Domino series)
	SDTV product (Picolo series)
	HDTV product (Picolo HD and Picolo.net series)
	Camera Link product (Grablink series)
	CoaXPress product (Coaxlink series)
	CoaXPress-over-Fiber product (Coaxlink series)
	Accessory product
	Software libraries
	Free software
Text	Description
Alphanumeric	Shortened product name (e.g. "Value12", "QSFP+") - Only for main products
Number	Product code w.o. prefix (e.g. 1625) - For accessories
Top border	Description
	Low performance camera interface (e.g. CXP-6, CL-85)
	High performance camera interface (e.g. CoF 10, CXP-12)
	Highest performance camera interface (e.g. CoF-25)
Badge	Description
	Preliminary
	Product on request
	Not recommended for new designs

Badge	Description
EOL	End-of-life product